

**Celadon Inc.**

**RCV-5000 IR to RS-232 Output Table**

**Device: Key Digital Flash Matrix Switcher KD-MSW8x4**

Infrared Remote Control: Philips PRONTO, Niles Intellicontrol

Infrared Code Format: NEC - Device ID: 7B02

Infrared Pronto Data File(s): See "IR Code Read Me - RCV-5000.txt" for complete description

Infrared Receiver: Celadon RCV-5000 Infrared to RS-232 Receiver

RCV-5000 Data File: keydig2\_r.hex

Data: 4800 Baud, 8, N, 1, ASCII Output

Standard Pinout

String: Ccxy

Where: x = (1-4)

y = (1-8)

Matrix Switcher Function (xy)	Pronto Button	RCV-5000 Output
11	0	CC11
12	1	CC12
13	2	CC13
14	3	CC14
15	4	CC15
16	5	CC16
17	6	CC17
18	7	CC18
21	8	CC21
22	9	CC22
23	10	CC23
24	11	CC24
25	12	CC25
26	13	CC26
27	14	CC27
28	15	CC28
31	16	CC31
32	17	CC32
33	18	CC33
34	19	CC34
35	20	CC35
36	21	CC36
37	22	CC37
38	23	CC38
41	24	CC41
42	25	CC42
43	26	CC43
44	27	CC44
45	28	CC45
46	29	CC46
47	30	CC47
48	31	CC48

Celadon, Inc.  
50 Mitchell Blvd.  
San Rafael, CA 94903  
Sales: (707) 648-1098  
Main Tel: (415) 472-1177  
Main Fax: (415) 472-1179  
[sales@celadon.com](mailto:sales@celadon.com)